



NiCE

SnapMirror CRSが実行されていないため、再同期に失敗しました。

https://kb-japan.netapp.com/on-prem/ontap/dp/SnapMirror/SnapMirror-KBs/SnapMirror_resync_failed_as_...

Updated: Thu, 17 Sep 2026 12:22:40 GMT

環境

- ONTAP 9
- 外部キー管理
- Configuration Replication Service (CRS)
- 1つ以上のSVMに対して設定されたSVMディザスタリカバリ (SVM DR)

問題

- SVM DR関係を再構成して [identity preserve](#) を [True](#) に設定する際に、`snapmirror resync` コマンドが以下のエラーを返しました：

```
Last Transfer Error: Config replication service error on cluster "local".
Reason: Configuration replication service is not active. Execute
"snapmirror show -destination-vserver <dst_vserver> -fields last-transfer-
error,unhealthy-reason -expand" to check if the constituent volumes have
encountered errors.
```

- CRSは `not running` と表示されます。これは、1つ以上のキーサーバーが利用できないためです。

```
>>> snapmirror config-replication status show
      Enabled: true
      Running: false
      Storage Status: warning
      Storage In Use: Unavailable
      Storage Remarks: Unable to free resources due to error One or more key servers are unavailable for Vserver . Use the "security key-manager external show-status -vserver " command to check the status of
                        by servers. Verify that the network configuration is correct.
      Vserver Streams: ok
```

- 外部キーマネージャの状態は、ステータスの詳細とともに利用できません
`SSL_PEER_VALIDATION` (`security key-manager external show-status` コマンド)